



www.2cdisplays.com.au


Extend IT

projector mount extension

This product has been specifically designed for use with the Hang IT projector mount, also from 2C.


The Extend IT has been innovatively designed as a modular unit. In this box are sufficient parts for either a projector mount 500mm below the ceiling or 1000mm below the ceiling. With a couple of simple modifications you can also customise the Extend IT to your own specific length anywhere between 125mm and 1000mm.

Extend IT mounting instructions




500mm

- 1 Attach the ceiling plate to the ceiling with appropriate fasteners.
- 2 Screw the pole with the joiner bolt onto the ceiling plate.
- 3 Attach the base plate to the extender pole using the M6 bolt supplied.
- 4 Attach the Hang IT to the base of the Extend IT using the M8 bolts supplied. See Pic A.
- 5 Follow the rest of the instructions on the Hang IT box.




Pic A



1000mm


- 1 Attach the ceiling plate to the ceiling with appropriate fasteners.
- 2 Screw the poles together using the supplied joiner.
- 3 Screw the 1000mm pole to the ceiling plate.
- 4 Attach the base plate to the extender pole using the M6 bolt supplied. See Pic B.
- 5 Attach the Hang IT to the base of the Extend IT using the M8 bolts supplied.
- 6 Follow the rest of the instructions on the Hang IT box.



Pic B

Handy Hints

- 1 You may adjust the total height of the post by cutting it with a hacksaw. Make sure that you only cut off the end with the 6.5mm hole. Then redrill the 6.5mm hole 60mm from the end. Do not cut the threaded end of the post. See Pic C.
- 2 The Extend IT uses Lock-Tite to secure the threaded ends of the poles. For the best result, screw each connection once, and once only. If you unscrew and re-screw a joint, you will reduce the effectiveness of the Lock-Tite. If you need to undo a joint, we recommend that you reapply Lock-Tite to the joint before reconnecting.



Pic C